



# DIGITAL MILLI OHM METER



**“CROWN” DIGITAL MILLI OHM METER** is useful for accurate measurement of low resistance of Copper Wire Conductors, Cables , Coil , Heater Element, Contact Resistance of Switch Relays etc. Four terminal measurement system ensures error free reading without effect of Test Lead Resistance.

### SPECIFICATION

**RANGE** - 0.1 mill Ohm to 199.9K Ohm in 7 Range

<u>RANGE</u>	<u>TEST CURRENT</u>
0 - 199.9m Ohm	1A
0 - 1. 999 Ohm	100 mA
0 - 19.99 Ohm	10 mA
0 - 199.9 Ohm	1 mA
0 - 1.999K Ohm	100 uA
0 - 19.99K Ohm	10 uA
0 - 199.9K Ohm	1 uA

<b>ACCURACY</b>	:	$\pm 0.2\% \pm 2$ Digit
<b>RESOLUTION</b>	:	1 In 1999 Count
<b>DISPLAY</b>	:	3 1/2 Digit 12.5mm Height LED.
<b>POWER</b>	:	230V AC $\pm 10\%$

For further details please contact :

## **CROWN ELECTRONIC SYSTEMS**

**AN ISO 9001:2000 CERTIFIED COMPANY**

**REGD. OFFICE :** JG-1/7A.VIKAS PURI, NEW DELHI - 110018

**Visit us at :** [www.Crownelectronicssystem.com](http://www.Crownelectronicssystem.com)

**E-mail :** [crownelectronicssystem@yahoo.com](mailto:crownelectronicssystem@yahoo.com)

**PH :** 64508650,64508649, 22995324

**CROWN OFFERS YOU A WIDE RANGE OF:** OSCILLOSCOPE , AUDIO OSCILLATOR , FUNCTION GENERATOR , DC REGULATED POWER SUPPLY, DIGITAL FREQUENCY COUNTER/ MILLI OHM METER/ pH METER/ DPM,s FOR V,A, Hz., AND WATT, VTVM, LCR METER, HIGH VOLTAGE BREAK DOWN TESTER, AF POWER OUTPUT METER, AND ALL OTHER INSTRUMENTS, COMPONENTS AND ACCESSORIES, FOR ELECTRONICS AND ELECTRICAL LAB.