

## CES - 202 AUTO

# 3½ DIGIT AUTO RANGING DIGITAL MILLI OHM METER

“CROWN” made 3½ DIGIT AUTO RANGING DIGITAL MILLI OHM METER is useful for accurate measurement of low resistance of copper wire conductors , cables , coil , heater element , contact resistance of switch relays etc. Four terminal measurement system ensures error free reading without effect of test lead resistance .



### SPECIFICATION

**RANGE** : 0.1 mill Ohm to 199.9K Ohm in 7 Range **AUTO / MANUAL** Selection

<u>RANGE</u>	<u>RESOLUTION</u>	<u>TEST CURRENT</u>
0 - 199.9 m Ohm	100 $\mu\Omega$	1A
0 - 1.999 Ohm	1m $\Omega$	100 mA
0 - 19.99 Ohm	10m $\Omega$	10 mA
0 - 199.9 Ohm	100m $\Omega$	1 mA
0 - 1.999 K Ohm	1 $\Omega$	100 $\mu$ A
0 - 19.99 K Ohm	10 $\Omega$	10 $\mu$ A
0 - 199.9 K Ohm	100 $\Omega$	1 $\mu$ A

**ACCURACY** :  $\pm 0.2\% \pm 2$  Digit

**RESOLUTION** : 1 In 1999 Count

**DISPLAY** : 3 ½ Digit 12.5 mm Height LED

**POWER** : 230V AC  $\pm 10\%$

**STANDARD ACCESSORIES** : Test Lead-Banana to Crocodile Clip  
One Set Of 4 Leads

(SPECIFICATIONS & DESIGN SUBJECT TO  
CHANGE WITHOUT PRIOR NOTICE)