



DIGITAL LINE FREQUENCY METER



SPECIFICATION

Frequency	:	30.00 Hz to 70.00 Hz
Display	:	4 digit , 7 segment , Bright , LED 12.5 mm High
Resolution	:	0.01 Hz
Accuracy	:	$\pm 0.1\%$ ± 1 Digit
Time Base	:	Quartz crystal based oscillator
Sampling Time	:	Precise 1 sec.
Input Voltage	:	150VAC to 300VAC
Temperature Coefficient	:	50 ppm / 0C
Size	:	A) 92 mm (H) X 92 mm (W) B) 46 mm (H) X 92 mm (W) C) 60 mm (H) X 100 mm (W)

CES - 205A - WALL MOUNTING DLF WITH 1.8" DISPLAY

Other Cabinet & Display Size also available against requirement .

CROWN ELECTRONIC SYSTEMS

69/2A, 2nd Floor, Najafgarh Road Indl. Area, Near Moti Nagar Crossing, New Delhi-15.

Phone: 011-6450 8649/50, 2599 5324, Tele Fax: 011-4501 3465

E-mail: crownelectronicssystem@yahoo.com, info@crownelectronicssystem.com

www.crownelectronicssystem.com