



CES - 52C

3 1/2 DIGIT DIGITAL MILLI OHM METER

“CROWN” made **DIGITAL MILLI OHM METER** is useful for accurate measurement of low resistance of copper wire conductors , cables , coil , heater element , contact resistance of switch relays etc. Four terminal measurement system ensures error free reading without effect of test lead resistance .



SPECIFICATION

RANGE : 0.1 milli Ohm to 199.9K Ohm in 7 Range

<u>RANGE</u>	<u>RESOLUTION</u>	<u>TEST CURRENT</u>
0 - 199.9 m Ohm	100 $\mu\Omega$	1A
0 - 1.999 Ohm	1m Ω	100 mA
0 - 19.99 Ohm	10m Ω	10 mA
0 - 199.9 Ohm	100m Ω	1 mA
0 - 1.999 K Ohm	1 Ω	100 μ A
0 - 19.99 K Ohm	10 Ω	10 μ A
0 - 199.9 K Ohm	100 Ω	1 μ A

ACCURACY : $\pm 0.2\% \pm 2$ Digit

RESOLUTION : 1 In 1999 Count

DISPLAY : 3 1/2 Digit 12.5 mm Height LED

POWER : 230V AC $\pm 10\%$

STANDARD ACCESSORIES : Test Lead-Banana to Crocodile Clip
One Set Of 4 Leads

(SPECIFICATIONS & DESIGN SUBJECT TO
CHANGE WITHOUT PRIOR NOTICE)